



India's largest manufacturer of Digital Inkjet Printers

# VERVE LED - VLR 2513

## SITE READINESS DOCUMENT



India's largest manufacturer of Digital Inkjet Printers

## Prerequisites for VERVE LED - VLR 2513

### Contents

1. Power Supply
2. Computer
3. Environment
4. Floor & Space

### Power Requirements

- Total Power Consumption is 7KW.
- Machine needs single phase AC 220V, 30Amps (+ / - 10%), 50/60Hz.
- Uninterrupted power supplies (flicker free) should be provided as it has digital circuit.
- Proper earthing should be required.
- Printer and computer must share same exclusive earthing.

### Computer

#### Minimum Requirements

- Intel Core i7
- 8 GB RAM
- Solid State Disk 128GB
- Hard Disk 1TB
- Video/Graphics Card 2G
- USB 2.0
- Windows 7 (64 bit) or Windows 10 (64bit)

**Notice:** If computer system configuration doesn't meet the above-mentioned specifications, then printer performance gets slow down (will affect the printing data transfer).

### Environment Requirements

- Room temperature should be maintained in the range of 18-28 degree Celsius with humidity 20-60% RH.
- There should not be air draught in the room
- Closed dust-free room exclusive for Printer

### Floor & Space

- **Machine Dimensions** : 4700 x 2660 x 1520 mm (LxWxH)
- **Packing Dimension** : 4830 x 2280 x 1840 mm (LxWxH)
- **Machine Net Weight** : ~1762kg
- **Machine Gross weight** : ~1962kg



India's largest manufacturer of Digital Inkjet Printers

## Room Dimension

**Room Dimension: 7000mm (L) X 3500mm (W) X 3000mm (H)**

**Note:** Width of the room entrance must be more than 2860 mm (including gantry) to easily move the machine inside in single piece.

Please find Site Plan layout in the next sheet.

## Site Layout

