



India's largest manufacturer of Digital Inkjet Printers

VERVE LED - VLY 2513

SITE READINESS DOCUMENT



India's largest manufacturer of Digital Inkjet Printers

Prerequisites for VERVE LED - VLY 2513

Contents

1. Power Supply
2. Computer
3. Environment
4. Floor & Space

Power Requirements

- Total Power Consumption is 7KW.
- Machine needs single phase AC 220V, 30Amps (+ / - 10%), 50/60Hz.
- Uninterrupted power supplies (flicker free) should be provided as it has digital circuit.
- Proper earthing should be required.
- Printer and computer must share same exclusive earthing.

Computer

Minimum Requirements

- Intel Core i7
- 8 GB RAM
- Solid State Disk 128GB
- Hard Disk 1TB
- Video/Graphics Card 2G
- USB 2.0
- Windows 7 (64 bit) or Windows 10 (64bit)

Notice: If computer system configuration doesn't meet the above-mentioned specifications, then printer performance gets slow down (will affect the printing data transfer).

Environment Requirements

- Room temperature should be maintained in the range of 18-28 degree Celsius with humidity 20-60% RH.
- There should not be air draught in the room
- Closed dust-free room exclusive for Printer



India's largest manufacturer of Digital Inkjet Printers

Floor & Space

- **Machine Dimensions** : 4900 x2680 x1620 mm (LxWxH)
- **Packing Dimension** : 5030 x2280 x 1890 mm (LxWxH)
- **Machine Net Weight** : ~1962kg
- **Machine Gross weight** : ~2162kg

Room Dimension

Room Dimension: 7000mm (L) X 3500mm (W) X 3000mm (H)

Note: Width of the room entrance must be more than 2680 mm (including gantry) to easily move the machine inside in single piece.

Please find Site Plan layout in the next sheet.



India's largest manufacturer of Digital Inkjet Printers

Site Layout

